




## LED Multi Signal Light featuring three flashing patterns for diverse use.

- · Flashing Pattern: 3 Patterns···Simulated Rotation, Strobe, Blinking.
- · Enhanced Illumination: Use of long-life, super bright LED.
- · Maintenance-free: No bulb replacement needed.
- · Energy Efficient: Low power consumption.
- · Extended Product Life: Longer life without the use of a motor.
- · Installation: Indoor: upright, inverted and sideways; Outdoors: upright only.
- · Available Colors: Red, Amber, Green, Blue.
- $\cdot$  Conforms to the CE requirements.
- · UL Listed (File No. E215660).

## Available by Special Order

· Silver Color Body

## **Dimensions**



## **KHE Type**

Model	Rated Voltage	Color	Power Consumption	Current	Luminosity
KHE-24	24V DC (no polarity)	Red	8.2W	340mA	10cd
		Amber	8.2W	340mA	15cd
		Green	10.1W	420mA	15cd
		Blue	21.6W	900mA	3cd